

# EAT•N

# Powerware

## Powerware 5110 Uninterruptible Power System

Product Focus

350-1500 VA power protection for PC,  
telephone and networking equipment



### Product Snapshot

Power Rating: 350-1500 VA

Voltage: 240 VAC

Frequency: 50 Hz

Configuration: Plug-and-play  
tower, under  
monitor, or 2U  
rackmount

Topology: Line-interactive

### Features

- Protect the integrity of your data and applications by shielding electronic equipment from power outages, surges, sags, undervoltage and overvoltage conditions.
- Save space with a compact design that can be deployed as a tower, under a computer monitor or in a rack.
- Protects loads on six outlets - three with surge suppression and battery backup, three with surge suppression only.
- Deliver consistent, clean output with automatic voltage regulation (AVR) that doesn't drain battery power.
- Extend UPS service life with user-replaceable batteries
- Phone line transient protector guards phone equipment from "back door" power surges.
- Stay informed of power problems and low battery conditions with audible alarms and remote alarm notification via e-mail, pager, the Web or SNMP.
- Deliver short-term mobile power with start-on-battery capability.
- USB port and cable are standard.
- Rest easy with a two-year full warranty, plus three year pro-rated warranty and \$50,000 load protection guarantee (Australia and New Zealand). Optional Fastfix Service Plan is available to provide repair and replacement coverage that goes beyond the provision of the warranty.

The Powerware 5110 UPS provides a layer of defence between your equipment and raw utility power. This line-interactive UPS constantly safeguards your systems from power outages, surges, sags, undervoltage and overvoltage conditions - and provides varying degrees of protection from other power problems as well. If utility power is interrupted, even briefly, the Powerware 5110 UPS transfers to battery power.

The Powerware 5110 UPS uses Automatic Voltage Regulation (AVR) to smooth out wide fluctuations in input voltage. If input voltage varies as much as 25% over or 23% under nominal voltage - which can easily happen when running on generator power or in severe environments - the Powerware 5110 UPS accepts this inconsistent voltage and delivers clean, consistent output for protected equipment.

AVR enables you to work through even the most frequent brownouts and power sags.

Unlike typical line-interactive systems, the Powerware 5110 UPS does not switch back and forth to battery power to accomplish this voltage regulation - which would shorten battery life and increase battery replacement costs. As a result, battery power is conserved for when you really need it.

The Powerware 5110 UPS occupies a small footprint - about the size of a dictionary for low power units (350-700VA), or a sleek tower for higher-rated models (1000-1500VA). This tower package fits easily under a monitor or can be rackmounted in only 2U of rack space.

# Technical Specifications

## POWERWARE 5110

Model Number	51100350A	51100500A	51100700A	51101000A	51101500A
Capacity	350VA/210W	500VA/300W	700VA/420W	1000VA/600W	1500VA/900W
Dimensions (mm) HxWxD	270x87x260	270x87x260	270x87x260	270x87x384	270x87x384
Unit Weight (kg)	5	6	8	12	12.5
Input Connection	1.8 metre line cord IEC to Australian 10Amp Plug				
Output Connection	6 Australian 10Amp Outlets (3 Battery Backup & Surge Protection, 3 Surge Protection only)				
Operation					
Input Voltage Range (on-line operation)	186 to 280 VAC				
Output Voltage Regulation on-line	216 to 260 VAC				
On Battery Output Voltage	Nominal -12% to +10%				
Frequency	50 Hz				
Lightning/Surge Protection	476 joules				
Safety	AS/NZS62040.1.1, AS/NZS60950, A-Tick				
EMI	AS/NZS62040.2, AS/NZSCISPR22, C-Tick				
Transfer Time to Battery/AC	2-6 msec. typical				
Battery Type	Sealed, maintenance free lead-acid battery				
Typical Backup Time	3 minutes at full rated load				
Internet/Phone/Fax Protection	RJ11				
Short Circuit Protection	Circuit Breaker				
Communication Port	USB				
Environmental					
Operation Temperature	0°C - 40°C				
Operation Relative Humidity	0 to 95% non condensing				
Storage Temperature	-15°C - 50°C				
Software	Powerware LanSafe Software is included free of charge				
Service Plans	Optional Extended Warranty and On Site Changeover service plans available				

Model	Load (VA)											
	80	170	250	330	420	550	650	850	1000	1200	1350	1500
51100350A	31	12	7	4								
51100500A	43	17	11	6	4							
51100700A	53	30	14	9	7	4	3					
51101000A	80	64	-	28	20	15	12	8	5			
51101500A	-	74	-	35	-	-	14	10	7	6	5	4

This guide provides typical application information. Battery run times are approximate and may vary with equipment, configuration, battery age, temperature, etc.

In the interests of continual product improvement all specifications are subject to change without notice.

Eaton, Powerware, Hot Sync, Advanced Battery Management, LanSafe, PowerVision, and FORESEER are trade names, trademarks, and/or service marks of Eaton Corporation or its subsidiaries and affiliates. © 2007 Eaton Corporation, All Rights Reserved.

**HEAD OFFICE**  
 Eaton Power Quality Pty Ltd  
 10 Kent Road  
 Mascot NSW 2020  
 Phone: +61 2 9693 9366  
 Fax: +61 2 8338 1159  
[www.powerware.com.au](http://www.powerware.com.au)

**SALES OFFICES**  
 Queensland  
 Phone: +61 7 3844 9728  
 Fax: +61 7 3217 2199

**Western Australia**  
 Phone: +61 8 9446 0520  
 Fax: + 61 8 9244 7466

**Victoria**  
 Phone: + 61 3 9706 5662  
 Fax: + 61 3 9794 9150

**AUCKLAND, New Zealand**  
 Phone: +64 9 579 8717

**Sales 1300 UPS UPS**  
**Service 1300 303 059**

**SOUTH AUSTRALIA**  
 Phone: +61 8 8347 3622  
 Fax: +61 8 8445 6328

**WELLINGTON New Zealand**  
 Phone: + 64 4 477 4717  
 Fax: +64 4 477 3691